

Circuit Breaker Distribution with Remote Control

New!



Instantly reboot, start or stop -48V telecom equipment in remote locations securely from your web browser or via program control. Eliminate overloads, brown-outs, blown breakers and other power problems before they occur, start devices in sequence automatically.

Ease of remote operation is made possible via numerous web browser control options of up to 8 breaker protected circuits. Remotely control power relays, choose from sequential on, all-off, selective circuit, or last state. In addition, an advanced custom control function is built-in, programmed via a BASIC style language that remotely initializes scripts without user intervention upon defined conditions such as: power-up, or when lock up is sensed via the "Auto-Ping" feature. Auto Ping continually monitors critical network devices, such as telecom equipment, servers and routers. If a device fails to respond after a user selectable number of pings, the power controller will automatically reboot it, or run a user's script with no user intervention. "Locked-up" devices are brought back to life instantly. Long distance service calls are averted.

Convenient monitoring via user-defined graphics and hyperlinks allow you to customize web pages. Programmable web links provide a seamless control panel of multiple systems comprising several distribution reboot units.

Features

- Remote control routers, telecom equipment, switches any -48VDC device, up to 15 amps.
 - An internal web server gives you manual control from anywhere in the world
 - Use scripts to automate control from remote locations via LAN or WAN
- The "Auto-Ping" feature intelligently reboots a machine, router, server, or other Ethernet device automatically
- Windows utility provides e-mail notification of logs and events. Also supports UNIX style SYSLOG
- Eight relays are individually controlled by scripts or web commands over Ethernet. Ethernet connection with static IP allows connection anywhere on your LAN or WAN
- Dual 50 Amp A/B input bus power four 15 Amp outputs for each bus, or wire inputs in parallel for an 8 circuit bus.
- All inputs and outputs are circuit breaker protected; 7, 10, 15 amp
- Universal 19" brackets accommodate center, back, or front rack mounting

Model	Circuit Capacity	Dimensions (H x D x W)	Weight (Lbs.)
DST-8-RB	8	1.75" x 11" x 17"	9.3 Lbs.

Preliminary specifications subject to change without notice.

NEWMAR[®]

Powering the Network

Newport Beach, CA USA

www.newmartelecom.com ■ 800-854-3906

Circuit Breaker Distribution with Remote Control

Specifications

Electrical

Input Supply Voltage 36-75VDC either A or B bus

Input Frequency: DC, 20% ripple permissible

A/B Input Breakers: 50A thermal, manual reset

Power Dissipation 10.3W Max (relays on) <3 W idle

Ethernet Interface: 10/100 autosensing, Static IP, TCP port selectable, 8 pin RJ-45 w/ internal FCC filtering

Input Terminal Rating: 100VDC 100A

Relay Contact Rating: 20A DC

Password Transmission: Secure authentication
Encrypted, base 64 Movable HTTP port for security

Output Circuit Breakers: 7, 10 or 15A thermal,
manual reset

Power Fail Hold-Over: 600ms minimum (all relays on)

Switches & Controls: Reset to factory default switch
Link, ACT (Relays On), Pwr LEDs

Power-Up Settings: Last relay settings, all relays off,
sequential on or run PLC script

Software Controls (via web or script): Individual
outlets on/off, all on

Mechanical

Dimensions: 11.0" x 17.0" x 1.75", 1U, 19" rack
mountable

Weight: 9.3 Lbs.

Enclosure Material: Cold rolled steel, no flammable
plastics, vented 4 sides

Environmental

Operating Temperature: -40° to 170°F, -34° to 77°C

Rear Panel View



Newport Beach, CA USA

Powering the Network

www.newmartelecom.com ■ 800-854-3906